

	SERIES	PART NUMBER	DESCRIPTION	Nº OF CONTACT	TYPE OF CONTACT	MAX. CONTACT LOAD AC1	MAX. CONTACT LOAD DC1	SOCKETS
General Purpose	RM	RM2010	Universal 8-Pin	2	Standard	10 A @ 250 V	0.5 A @ 110 V	SMB20
		RM3010	Universal 11-Pin	3	Standard	10 A @ 250 V	0.5 A @ 110 V	SMB30
		RM4010	Square Base, 4-Pole	4	Standard	10 A @ 250 V	0.5 A @ 110 V	SMT40
	RP	RP2010	Square Base, AC Power	2	High Power	16 A @ 400 V *	0.5 A @ 110 V	SPT30
		RP3010	Square Base, AC Power	3	High Power	16 A @ 400 V *	0.5 A @ 110 V	SPT30
	RQ	RQ1010	Miniature, AC Power	1	High Power	16 A @ 250 V *	0.5 A @ 110 V	SQR10
		RQ2010	Miniature, AC Power	2	Standard	10 A @ 250 V	0.5 A @ 110 V	SQB20
		RQ4110	Miniature, 14-Pin Plug-in	4	Standard	5 A @ 250 V	0.2 A @ 110 V	SQB40
RF	RF1010	Interface	1	Standard	10 A @ 250 V	0.5 A @ 110 V	SFB10	
	RF2110	Interface	2	Standard	5 A @ 250 V	0.5 A @ 110 V	SFB20	
Bifurcated Contacts Low Level Loads	RM	RM2117	Universal 8-Pin Plug-in	2	C Twin 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SMB20
		RM3117	Universal 11-Pin Plug-in	3	C Twin 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SMB30
		RM2317	Universal 8-Pin Plug-in	2	C Twin 10u Gold	6 A @ 250 V	6 A @ 30 V	SMB20
		RM3317	Universal 11-Pin Plug-in	3	C Twin 10u Gold	6 A @ 250 V	6 A @ 30 V	SMB30
	RQ	RQ2117	Miniature	2	C Twin 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SQB20
		RQ2317	Miniature	2	C Twin 10u Gold			
	RF	RF1217	Interface Twin	1	C Twin, 3u Gold	6 A @ 250 V	6 A @ 30 V	SFB10
		RF1317	Interface Twin	1	C Twin, 10u Gold	6 A @ 250 V	6 A @ 30 V	SFB10
		RF2310	Interface Twin	2	C Twin, 10u Gold			
		RF1222LE	Interface Twin N.O.	1	C Twin, D. Polarity 3u Gold	6 A @ 250 V	6 A @ 30 V	SFB10
Bifurcated Contacts Current Level Loads	RQ	RQ2021	Universal 8-Pin Plug-in	2	Estándar + Bifurcated	10 A @ 250 V	6 A @ 30 V	SQB20
Open Contacts	RM	RM2014	Universal 8-Pin Plug-in	2	C. Open, Dc Load Switching	10 A @ 250 V	1.2 A @ 110 V	SMB20
		RM3014	Universal 11-Pin Plug-in	3	C. Open, Dc Load Switching	10 A @ 250 V	1.2 A @ 110 V	SMB30
	RP	RP3014	Square Base	3	C. Open, Dc Load Switching	16 A @ 400 V	1.2 A @ 110 V	SPT30
Flag Not Available	RQ	RQ2014	Universal 8-Pin Plug-in	2	C. Open, Dc Load Switching	10 A @ 250 V	0.8 A @ 110 V	SQB20
Flag Available	RF	RF1014	Interface N.O.	1	C. Open, Dc Load Switching	10 A @ 250 V	0.8 A @ 110 V	SFB10
		RF2114	Interface N.O.	2	C. Open, Dc Load Switching	5 A @ 250 V	0.8 A @ 110 V	SFB20
Double Make	RM	RM1015	11-Pin, DC Power	1	D. Make, Dc Load Switching	10 A @ 250 V	7 A @ 110 V	SMB30
DC Load Switching		RM2015	Square Base, DC Power	2	D. Make, Dc Load Switching	10 A @ 250 V	7 A @ 110 V	SMT40
	RP	RP1015	Square Base, DC Power	1	D. Make, Dc Load Switching	16 A @ 400 V *	7 A @ 110 V	SPT30
Flag Not Available	RQ	RQ1015	Miniature, DC Power	1	D. Make, Dc Load Switching	10 A @ 250 V	6 A @ 110 V	SQB20
Latching	RM	RM2019	11-Pin Plug-in	2	Remanence [Latching Relay]	10 A @ 250 V	0.5 A @ 110 V	SMB30
		RM3019	Square Base, 14-Pin	3	Remanence [Latching Relay]	10 A @ 250 V	0.5 A @ 110 V	SMT40
		RP	RP2019	Square Base	2	Remanence [Latching Relay]	10 A @ 400 V	0.5 A @ 110 V
LED Not Available	RQ	RQ2119	Miniature	2	Remanence [Latching Relay]	5 A @ 250 V	0.2 A @ 110 V	SQB40
Magnetic Blow-out	RM	RM1016	11-Pin Plug-in, High DC Load	1	D. Make & B. Magnetic, Dc Load Switching	10 A @ 250 V	10 A @ 220 V	SMB30
	RP	RP1016	Square Base, High DC Load	1	D. Make & B. Magnetic, Dc Load Switching	16 A @ 400 V	10 A @ 220 V	SPT30
		RP2016	Square Base, High DC Load	2	B. Magnetic, Dc Load Switching	16 A @ 250 V	7 A @ 110 V	SPT30
Sensitive	RM	RM1111	Universal 11-Pin Plug-in	1	Sensitive 250mw 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SMB30
		RM2112	Universal 11-Pin Plug-in	2	Sensitive 500mw 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SMB30
		RM3113	Universal 11-Pin Plug-in	3	Sensitive 800 Mw Open 0,2u Gold	6 A @ 250 V	6 A @ 30 V	SMB30
Flag Not Available	RQ	RQ2112	Universal 8-Pin Plug-in	2	Sensitive 500mw 0,2u Gold	5 A @ 250 V	5 A @ 30 V	SQB40
Lamp Switching High Inrush Current	RQ	RQ1018	Miniature, FASTON 187	1	C. Open Wolfram	10 A @ 250 V	0.5 A @ 110 V	SQB20
Railway Applications	RR	RR3010	Universal 11-Pin Plug-in	3	Iec 61810 / En 60947	6 A @ 250 V	6 A @ 30 V	SMB30
		RR2010	Universal 8-Pin Plug-in	2	Iec 61810 / En 60948	10 A @ 250 V	10 A @ 30 V	SQB20
		RR2117	Miniature, Twin Contacts	2	Iec 61810 / En 60949	6 A @ 250 V	6 A @ 30 V	SQB20
		RR4110	Miniature, 14-Pin Plug-in	4	Iec 61810 / En 60950	5 A @ 250 V	0.2 A @ 110 V	SQB20
Solid State Relay	RS	RS1814	Instantaneuos	1	Solid State Ac (Unlimited Ops.)	3 A @ 250 V	N/A	SFB10
		RS1914	Zero-cross	1	Solid State Ac (Unlimited Ops.)	3 A @ 250 V	N/A	SFB10
		RS1614	Common Negative	1	Solid State Dc (Unlimited Ops.) Npn	N/A	2 A @ 50 V	SFB10
		RS1714	Common Positive	1	Solid State Dc (Unlimited Ops.) Pnp	N/A	2 A @ 50 V	SFB10
Multivoltage LH	RM	RM2010	Universal 8-Pin	2	24 ... 240 Vdc/Vac	10 A @ 250 V	0.5 A @ 110 V	SMB20
		RM3010	Universal 11-Pin	3	24 ... 240 Vdc/Vac	10 A @ 250 V	0.5 A @ 110 V	SMB30
		RM4010	Square Base, 4-Pole	4	24 ... 240 Vdc/Vac	10 A @ 250 V	0.5 A @ 110 V	SMT40
	RP	RP2010	Square Base, AC Power	2	24 ... 240 Vdc/Vac	16 A @ 400 V *	0.5 A @ 110 V	SPT30
		RP3010	Square Base, AC Power	3	24 ... 240 Vdc/Vac	16 A @ 400 V *	0.5 A @ 110 V	SPT30
	RQ	RQ1010	Miniature, AC Power	1	24 ... 240 Vdc/Vac	16 A @ 250 V *	0.5 A @ 110 V	SQR10
		RQ2010	Miniature, AC Power	2	24 ... 240 Vdc/Vac	10 A @ 250 V	0.5 A @ 110 V	SQB20
		RQ4110	Miniature, 14-Pin Plug-in	4	24 ... 240 Vdc/Vac	5 A @ 250 V	0.2 A @ 110 V	SQB40
	RF	RF1010	Interface	1	24 ... 240 Vdc/Vac	10 A @ 250 V	0.5 A @ 110 V	FG5696
		RF2110	Interface	2	24 ... 240 Vdc/Vac	5 A @ 250 V	0.5 A @ 110 V	FG5697
STB	RT1010LN0	6,2 mm Relay	1	24 ... 240 Vdc/Vac	6 A @ 250 V		STB10H	
Time Cube	RM	TMB	8-Pin/11-Pin Plug-in Timer Module	2 or 3	Switch Off Delay	10 A @ 250 V	0.5 A @ 110 V	SMB20/SMB30
		TMD	8-Pin/11-Pin Plug-in Timer Module	2 or 3	Impulse On	10 A @ 250 V	0.5 A @ 110 V	SMB20/SMB30
		TMA	8-Pin/11-Pin Plug-in Timer Module	2 or 3	On Delay	10 A @ 250 V	0.5 A @ 110 V	SMB20/SMB30
		TMC	8-Pin/11-Pin Plug-in Timer Module	2 or 3	One Shot	10 A @ 250 V	0.5 A @ 110 V	SMB20/SMB30
		TMS	8-Pin/11-Pin Plug-in Timer Module	2 or 3	Blinker	10A @ 250 V	0.5 A @ 110 V	SMB20/SMB30
Slim Relay	STB	RT1010NN0	6,2 mm Relay 12 VDC	1	Slim Relay For Pcb	6 A @ 250 V		STB10S
		RT1010NN0	6,2 mm Relay 24 VDC	1	Slim Relay For Pcb	6 A @ 250 V		STB10L
		RT1010NN0	6,2 mm Relay 60 - 240 VDC	1	Slim Relay For Pcb	6 A @ 250 V		STB10U